

Personal LBS Tracker User Manual



In order to install and operate the LBS tracker in right method and properly, please read this Fast Installation Instruction & User Manual before installation, thank you.

Package & Accessories

Power Charger *1; Ear-Phone*1; User Manual *1; Warranty Card*1;

Functions

Living Tracking, Orbit recorded;

9 SOS Emergency Contact Numbers;

Tracking with both Mobile phone message and internetCall bound
Number and talking each other(with Earphone)

Battery volume checking,Low electricity Alarm ,Saving-Electricity
Mode setting,Battery Last many days

Call back through Voice

Supporting Android,Apple Mobile Phone APP to Control

Technical Parameter

GMS frequency: 900/1800MHz /850/1900MHz;

GPRS: Class12,TCP/IP;

Working Temperature: -2℃ - +70℃ ;

Working Humidity: 20%-80%RH;

Dimension: 44.0(L)*37.0(W)*12.0(H)mm;

Net weight: 26g;

Internal Battery : 500mah

Installation Instructions

Before Installation

Open the package, please look over whether the part number is correct and whether accessories complete, if not, please contact your distributor for further assistance;

Choose correct SIM card, a GSM net SIM card will be needed to insert into the terminal, please consult distributors options for further use;

Please Note:

Plug the SIM card Before Turn on the Device

Please make sure that the SIM card has enough credit;

Special GPRS data SIM Card suggested (GSM network only);

Terminal Operations

Start-up/Shut-down

Start-up: insert the SIM card, the terminal will start up;

Shut-down: take out the SIM card, the terminal will shut down;

Terminal parameters settings

All beginning letters in each parameters' commands shall use upper-case letters, all punctuations shall be English punctuation, By sending enquiry commands to the terminal, corresponding contents will be replied.

SOS Emergency Phone Call Number Setting

Send SMS: **#711#Emergency Contact Phone Number#0000#1##**

Initial password is 0000, command start with *

e.g.: **#711#123456789#0000#1##**

#711#987654321#0000#2##

Reply: **Config OK,successfully**

Reply: **Password ER, Failed**

Up to 9 Numbers can be set as Emergency phone calls.,serious number, 1-9

Get Terminal Position by SMS

Send SMS: **6660000** to terminal, it will reply the terminal current geography location

e.g.: south east 30 meters, ABC company, Meilong Rd, Shenzhen, Guangdong Province,China.

Send SMS:888000 to terminal,it will reply the Google link of the terminal current geography location.

Phone Calling

Call the phone number in tracker, if both have earphone, then phone calling function will be activated automatically, you can talk over phone with each other.

Call-Back

Send message"01" to turn on the call-back function

Send message"02" to turn on the call-back function

When Voice around the Device reach 60 Decibels,It will call the pre-set mobile phone number

SOS Alarm

Press the SOS button and last 3 seconds, the SOS Alarm will be send to platform and cellphone automatically.

Power Saving Mode Setting

Send the following SMS command to tracker, and once Config OK replied, then setting is successful.

Super Power Saving Mode **#730#37#1#0000##** , 8 Days Stand by.

Medium Power Saving Mode **#730#32#1#0000##** , 5 Days Stand by.

Normal Power Saving Mode **#730#30#1#0000##** , 3 Days Stand by.

Battery volume checking

Send "**bat**" to the sim card in the device.you will get a message how much battery volume left.

Like: **battery:100%**

Password Modification

Send SMS: # 770#New password(4 digits) #Presious password
(4 digits)##

e.g.: #770#1111#0000##

Initial password is 0000

New password is 1111

Live Tracking Monitoring Platform

Web Address: yun.gps112.net

If you already have a login account and password information, you can login our platform directly, or please contact your distributor and ask them to open you an account and provide you the password. Input the address link in your computer browser, input the account and password, then login to your service platform. About the use method of platform, please ask your distributor for Service Platform User Manual.

Download APP for Cell phone



LBS VEHICLE TRACKING TERMINAL WARRANTY CARD

Please Note:

Any upgrade of this products later on , notifications will only be sent to distributors;

Any changes on appearance or colour, pictures are only for information, take practicality as standard;

The warranty card only suits the following IMEI terminal;

Please keep the warranty card safe, also show the warranty card and original purchase receipt before repair services;

Specific warranty range as follow;

This warranty card is a basic access to repair service, please fill out the table carefully and keep it safe.

User Name		Contact phone No.	
Contact Address			
Part Number		IMEI Number	
Purchase Date		Receipt Number	
Distributor Name			
Distributor Address			
Distributor Phone			

1.From Purchase date, 1 year repair service for products crash due to products reason.

2.Any of following situations are not included in warranty range, but provide paid repair services.

Warranty period expired;

Damages caused by unauthorized tear down or repair;

Inundate, damage, PCB burnt due to improper act;

Terminal out cover, screen, antennas damages due to use;

Terminal inside IMEI's been pluck away or unable to read;

Warranty card any content is not in accordance with the terminal,

or warranty card has been modified by unauthorized;

Damages caused by force majeure;